

Specifications



Eaton 197213

Eaton Moeller® series EASY Control relays easyE4 with display (expandable, Ethernet), 24 V DC, Inputs Digital: 8, of which can be used as analog: 4, screw terminal

General specifications

PRODUCT NAME	Eaton Moeller® series EASY Control relay
CATALOG NUMBER	197213
EAN	4015081939466
PRODUCT LENGTH/DEPTH	58 mm
PRODUCT HEIGHT	90 mm
PRODUCT WIDTH	72 mm
PRODUCT WEIGHT	0.2 kg
COMPLIANCES	Eaton supports the product until its end of life

CERTIFICATIONS

CSA-C22.2 No. 61010
EN 61010
IEC/EN 61000-6-2
IEC 60068-2-27
IEC 60068-2-30
IEC/EN 61000-4-2
CULus per UL 61010
IEC 60068-2-6
IEC/EN 61000-6-3
IEC/EN 61131-2
EN 50178
UL Listed
UL Category Control No.:
NRAQ, NRAQ7
UL File No.: E205091
DNV GL
CE
UL hazardous location
class I
UL hazardous location
division 2
UL hazardous location
group A (acetylene)
UL hazardous location
group B (hydrogen)
UL hazardous location

	group C (ethylene) UL hazardous location group D (propane)
CATALOG NOTES	Accuracy of the real-time clock depending on ambient air temperature - fluctuations of up to ± 5 s/day (± 0.5 h/year) are possible
MODEL CODE	EASY-E4-DC-12TC1

General	
DEGREE OF PROTECTION	IP20
DISPLAY TEMPERATURE - MIN	0 °C
DISPLAY TEMPERATURE - MAX	55 °C
DISPLAY TYPE	Monochrome
DUTY FACTOR	100 % (Inductive load to EN 60947-5-1, With external suppressor circuit) 100 % (Inductive load to EN 60947-5-1, Without external suppressor circuit, $T_{0.95} = 15$ ms, $R = 48 \Omega$, $L = 0.24$ H) 100 % (Inductive load to EN 60947-5-1, Without external suppressor circuit, DC-13, $T_{0.95} = 72$ ms, $R = 48 \Omega$, $L = 1.15$ H)
FREQUENCY COUNTER	Cable length: ≤ 20 m (screened, Digital inputs 24 V DC) Number: 4 (I1, I2, I3, I4 - Digital inputs 24 V DC) Pulse pause ratio: 1:1 (Digital inputs 24 V DC) Pulse shape: Square (digital inputs 24 V DC) Counter frequency: 5 kHz (Digital inputs 24 V DC)
INSULATION RESISTANCE	According to EN 50178, EN 61010-2-201, UL61010-2-201, CSA-C22.2 NO. 61010-2-201
MOUNTING METHOD	Screw fixing using fixing brackets ZB4-101-GF1 (accessories) Top-hat rail fixing

Features & Functions	
FEATURES	Parallel connection of transistor outputs with resistive load, inductive load with external suppressor circuit, combination within a group - Group 1: Q1 to Q4 Networkable (Ethernet) Expandable Display indication of 6 lines x 16 characters
FITTED WITH:	Keypad Display Real time clock Timer
FUNCTIONS	Thermal cutout
INDICATION	LCD-display used as Output status indication of Transistor outputs LCD-display used as status indication of Digital inputs 24 V DC

	(according to IEC/EN 60715, 35 mm) Front build in possible Wall mounting/direct mounting Rail mounting possible
OPERATING FREQUENCY	Dependent on the cycle time of the basic device Dependent on the cycle- and transmission-time of the expansion devices Depending on the suppressor circuit (Inductive load to EN 60947-5-1, With external suppressor circuit, Max. switching frequency, max. duty factor)
OVERVOLTAGE CATEGORY	III
POLLUTION DEGREE	2
PRODUCT CATEGORY	Control relays easyE4
PROTOCOL	TCP/IP MODBUS
RESIDUAL CURRENT	0.1 mA (on signal "1" per channel)
RESIDUAL RIPPLE	5 % (transistor outputs) ≤ 5 %
RESOLUTION	<ul style="list-style-type: none"> • 1 min (Range H:M) • 1 s (Range M:S) • 12 Bit (value 0 - 4095, Analog inputs) • 5 ms (Range S)
SOFTWARE	EASYSOFT-SWLIC/easySoft
TYPE	easyE4 base device
USED WITH	easyE4
VOLTAGE TYPE	DC

Ambient conditions, mechanical

DROP AND TOPPLE	50 mm Drop height, Drop to IEC/EN 60068-2-31
HEIGHT OF FALL (IEC/EN 60068-2-32) - MAX	0.3 m
MOUNTING POSITION	Vertical Horizontal
SHOCK RESISTANCE	15 g, Mechanical, according to IEC/EN 60068-2-27, Half-sinusoidal shock 11 ms, 18 Impacts
VIBRATION RESISTANCE	10 - 57 Hz, 0.15 mm constant amplitude 57 - 150 Hz, 2 g constant acceleration According to IEC/EN 60068-2-6

Climatic environmental conditions

AIR PRESSURE	795 - 1080 hPa (operation)
AMBIENT OPERATING TEMPERATURE - MIN	-25 °C
AMBIENT OPERATING TEMPERATURE - MAX	55 °C
AMBIENT STORAGE TEMPERATURE - MIN	-40 °C
AMBIENT STORAGE TEMPERATURE - MAX	70 °C
ENVIRONMENTAL CONDITIONS	Condensation: prevent with appropriate measures Clearance in air and creepage distances according to EN 50178, EN 61010-2-201, UL61010-2-201, CSA-C22.2 NO. 61010-2-201
RELATIVE HUMIDITY	5 - 95 % (IEC 60068-2-30, IEC 60068-2-78)

Electro magnetic compatibility

AIR DISCHARGE	8 kV
BURST IMPULSE	According to IEC/EN 61000-4-4 2 kV, Supply cable 2 kV, Signal cable
CONTACT DISCHARGE	6 kV
ELECTROMAGNETIC FIELDS	3 V/m at 1.4 - 2 GHz (according to IEC EN 61000-4-3) 10 V/m at 0.8 - 1.0 GHz (according to IEC EN 61000-4-3) 1 V/m at 2.0 - 2.7 GHz (according to IEC EN 61000-4-3)
IMMUNITY TO LINE-CONDUCTED INTERFERENCE	10 V (according to IEC/EN 61000-4-6)
RADIO INTERFERENCE CLASS	Class B (EN 61000-6-3)
SURGE RATING	0.5 kV, Supply cables, symmetrical, power pulses (Surge), EMC According to IEC/EN 61000-4-5, power pulses (Surge), EMC 1 kV, Supply cables, asymmetrical, power pulses (Surge), EMC
VOLTAGE DIPS	20 ms ≤ 10 ms, Bridging voltage dips

Terminal capacities

TERMINAL CAPACITY	0.2 - 4 mm ² (AWG 22 - 12), solid 0.2 - 2.5 mm ² (22 - 12 AWG), flexible with ferrule
SCREWDRIVER SIZE	3.5 x 0.8 mm, Terminal screw
TIGHTENING TORQUE	0.6 Nm, Screw terminals

Electrical rating

CONVENTIONAL THERMAL CURRENT ITH OF AUXILIARY CONTACTS (1-POLE, OPEN)	0.5 A
--	-------

HEAT DISSIPATION	3.4 W (at 24 V DC)
------------------	--------------------

INRUSH CURRENT	12.5 A (for 6 ms)
----------------	-------------------

POWER CONSUMPTION	2 W
-------------------	-----

POWER LOSS	2 W
------------	-----

RATED OPERATIONAL VOLTAGE	24 V DC (-15 %/+ 20 % - power supply) 24 V DC (transistor outputs) 20.4 - 28.8 V DC (Transistor outputs) 24 V DC (digital inputs) 20.4 - 28.8 V DC
------------------------------	---

SUPPLY CURRENT	24/44 mA, Normally/max., On 1 signal, Transistor outputs 18/32 mA, Normally/max., On 0 signal, Transistor outputs
----------------	--

SUPPLY VOLTAGE AT AC, 50 HZ - MIN	0 VAC
--------------------------------------	-------

SUPPLY VOLTAGE AT AC, 50 HZ - MAX	0 VAC
--------------------------------------	-------

SUPPLY VOLTAGE AT DC - MIN	20.4 VDC
-------------------------------	----------

SUPPLY VOLTAGE AT DC - MAX	28.8 VDC
-------------------------------	----------

Communication

CONNECTION TYPE	Screw terminal Ethernet: RJ45 plug, 8-pole
-----------------	---

DATA TRANSFER RATE	10/100 MBit/s
--------------------	---------------

Short-circuit rating

SHORT-CIRCUIT CURRENT	6.8 A, Transistor outputs
-----------------------	---------------------------

SHORT-CIRCUIT PROTECTION	≥ 1 A (T), Fuse, Power supply Yes, electronic (Q1 - Q4), Transistor outputs
-----------------------------	---

SHORT-CIRCUIT TRIPPING CURRENT	$0.7 \leq I_e \leq 1.7$ per output, For $R_a \leq 10$ m Ω , Depending on number of active channels and their load, Transistor outputs
-----------------------------------	--

Cable

CABLE LENGTH	≤ 30 m, screened, Analog inputs 100 m, unscreened, Digital inputs 24 V DC
--------------	---

CABLE TYPE	CAT5
------------	------

Input/Output

ACCURACY

± 2 %, (I7, I8) ± 0.12 V, of actual value, within a single device (Analog Inputs)
 ± 3 %, of actual value, two easy devices (Analog Inputs)
 ± 2 s/day, Real-time clock to inputs (± 0.2 hYear)
 ± 1 %, Repetition accuracy of timing relays (of values)

CONVERSIONS

Each CPU cycle, Analog inputs

DELAY TIME

0.015 ms typ., Digital inputs 24 V DC (I1 - I8), Delay time from 1 to 0, Debounce OFF
 20 ms typ., Digital inputs 24 V DC (I1 - I8), Delay time from 1 to 0, Debounce ON
 0.015 ms typ., Digital inputs 24 V DC (I1 - I8), Delay time from 0 to 1, Debounce OFF
 20 ms typ., Digital inputs 24 V DC (I1 - I8), Delay time from 0 to 1, Debounce ON

INCREMENTAL COUNTER

Pulse pause ratio: 1:1
 Pulse shape: Square
 Value range: -2147483648 to +2147483647
 Number of counter inputs: 2 (I1 + I2, I3 + I4)
 Signal offset: 90°
 Counter frequency: ≤ 5 kHz

INCREMENTAL ENCODER

Cable length: ≤ 20 m (screened)

INPUT

Voltage (DC)

INPUT CURRENT

1 mA (Analog inputs)
 3.3 mA (I1 - I4, at 24 V DC, at signal 1)
 2.2 mA (I5 - I8, at 24 V DC, at signal 1)
 80 mA

INPUT IMPEDANCE

13.3 kΩ

INPUT VOLTAGE

Status 0: ≤ 15 V DC (I1 - I4, Digital inputs, 24 V DC)
 Status 0: ≤ 8 V DC (I5 - I8, Digital inputs, 24 V DC)
 Status 1: ≥ 15 V DC (I1 - I4,

Safety

EXPLOSION SAFETY CATEGORY FOR GAS

None

POTENTIAL ISOLATION

Between Transistor outputs and Ethernet: yes
 Between Digital inputs 24 V DC and Ethernet: yes
 Between Transistor outputs and control buttons: yes
 Between Transistor outputs and Power supply: yes
 Between Analog inputs and Outputs: yes
 Between Transistor outputs and expansion devices: yes
 Between Digital inputs 24 V DC and expansion devices: yes
 Between Analog inputs and expansion devices: yes
 Between Digital inputs 24 V DC: no
 Between Transistor outputs and Inputs: yes
 Between Transistor outputs: no
 Between Digital inputs 24 V DC and Power supply: no

Between Analog inputs: no

Between Analog inputs and Memory card: no
 Between Transistor outputs and Memory card: yes
 Between Digital inputs 24 V DC and Outputs: yes
 Between Analog inputs and Ethernet: yes
 Between Digital inputs 24 V DC and Memory card: no

Between Analog inputs and Power supply: no

PROTECTION AGAINST POLARITY REVERSAL

For transistor outputs (Caution: A short circuit will result if 0 V/earth is applied to the outputs in the event that the supply

	Digital inputs, 24 V DC Signal 0: ≤ 5 V DC (I1 - I8, Digital inputs, 24 V DC)
LAMP LOAD	Max. 3 W (without Rv per channel)
NUMBER OF INPUTS (ANALOG)	0 4
NUMBER OF INPUTS (DIGITAL)	8
NUMBER OF OUTPUTS (ANALOG)	0
NUMBER OF OUTPUTS (DIGITAL)	4
OUTPUT	Parallel connection of max. 4 Transistor outputs 2 A, Max. total current, Outputs 4 Transistor Outputs Voltage Current
OUTPUT VOLTAGE	$U = U_e - 1$ V (signal 1 at $I_e =$ 0.5 A, transistor outputs) Max. 2.5 V (at status 0 per channel, transistor outputs)
RAPID COUNTER INPUTS	1:1 (Pulse pause ratio) 10 kHz, Counter frequency ≤ 20 m (cable length, screened) -2147483648 - 2147483647 (value range) Square (pulse shape) Number: 4 (I1, I2, I3, I4 - Digital inputs 24 V DC)
SIGNAL RANGE	0 - 10 V DC, Analog inputs
UTILIZATION FACTOR	0.25 (Inductive load to EN 60947-5-1, Without external suppressor circuit, DC-13, $T_{0.95} = 72$ ms, $R = 48 \Omega$, $L = 1.15$ H) 0.25 (Inductive load to EN 60947-5-1, Without external suppressor circuit, $T_{0.95} = 15$ ms, $R =$ 48Ω , $L = 0.24$ H) 1 (Inductive load to EN 60947-5-1, With external suppressor circuit)

	voltage is connected to the wrong poles) Yes, for supply voltage (Siemens MPI optional)
EXPLOSION SAFETY CATEGORY FOR DUST	None

Design verification

EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID	0 W
HEAT DISSIPATION CAPACITY PDISS	0 W
HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID	0 W
RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN)	0 A
STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS	2 W
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Meets the product standard's requirements.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.

Resources

APPLICATION NOTES	eaton-easye4-aws-ap050027-en-us.pdf
BROCHURES	easy E4 control relay-brochure
CATALOGUES	eaton-product-overview-for-machinery-catalogue-ca08103003zen-en-us.pdf
CHARACTERISTIC CURVE	eaton-electrical-timers-easy-control-relays-characteristic-curve-002.eps
DECLARATIONS OF CONFORMITY	DA-DC-00005056.pdf DA-DC-00005049.pdf
DRAWINGS	eaton-modular-plc-starter-kit-dimensions.eps eaton-general-easy-control-relays-symbol-002.tif eaton-modular-plc-easy-control-relays-3d-drawing.eps
ECAD MODEL	DA-CE-ETN.EASY-E4-DC-12TC1
INSTALLATION INSTRUCTIONS	IL050020ZU
INSTALLATION VIDEOS	Video easy E4 control relay Control relay easyE4: The new generation
MANUALS AND USER GUIDES	MN050009_EN
MCAD MODEL	DA-CS-uc_12rc1 DA-CD-uc_12rc1
MULTIMEDIA	How to process SmartWire-DT modules using the EASY-COM-SWD-C1 module connected to an easyE4? How to connect the Remote Touch Display EASY-RTD to the easyE4? easyE4 SmartWire-DT module with Remote Touch Display and RMQ multi color indicator

10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

	Handling of the data logger as a ring buffer with the easyE4 using the ST programming language. How to connect the easyE4 to the touch panel XV-102 for easy? - 5 Steps How to process ModbusRTU devices with the EASY-COM-RTU-M1 module on an easyE4?
PRODUCT NOTIFICATIONS	MZ049014EN
SALES NOTES	TT-197213 EASY-E4-DC-12TC1 -de DE eaton-control-relay-easye4-flyer-fl050007en-en-us.pdf eaton-easy-remote-touch-display-flyer-fl048004en-en-us.pdf

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc
 Eaton House
 30 Pembroke Road
 Dublin 4, Ireland
 Eaton.com

© 2025 Eaton. All Rights Reserved.

Follow us on social media to get the latest product and support information.

